



INSTRUCTIONS FOR CHARGER AND BATTERIES SAVE THESE INSTRUCTIONS

This manual contains important safety and operating instruction for Lincoln Models 1215 and 1215A Battery Charger. Battery charger uses a standard cigarette lighter plug.

1. Before using this battery charger, read all instructions and cautionary markings on Battery Charger, Battery Pack, and product using battery.
 2. **CAUTION:** To reduce the risk of injury, Lincoln Model 1215 or 1215A Chargers should only be used to charge Lincoln battery pack Model 1201. Other types of batteries may burst causing personal injury and damage. Do not charge Lincoln Model 1201 Battery Packs with any other charger.
 3. Do not expose charger to moisture (rain, snow or frost).
 4. Do not abuse cord. Never carry charger by cord or yank it to disconnect from battery outlet. Pull by plug rather than cord when disconnecting charger. Replace damaged or worn power cord and strain reliever immediately.
 5. Make sure cord is located so that it will not be stepped on, tripped over, or otherwise subjected to damage or stress.
 6. Do not operate charger if it has received a sharp blow, been dropped, or otherwise damaged in any way, take it to a qualified serviceman.
 7. Do not disassemble charger or battery pack. Take it to a qualified serviceman when service or repair is required. Incorrect reassembly may result in risk of electrical shock or fire.
 8. Unplug charger from battery outlet before attempting any maintenance or cleaning to reduce risk of electric shock.
 9. Charge the battery pack in a well ventilated place, do not cover the charger and battery with a cloth, etc., while charging.
 10. Do not store the charger or battery packs in locations (such as a metal tool shed, or a car in the summer) where the temperature may reach or exceed 122° F (50° C), which can lead to deterioration of the storage battery.
 11. Do not charge battery pack when the temperature is BELOW 32° F (0° C) or ABOVE 104° F (40° C). This is very important for proper operation.
 12. Do not incinerate battery pack. It can explode in a fire.
 13. Do not short across the terminals of the battery pack. **EXTREMELY HIGH TEMPERATURES COULD CAUSE PERSONAL INJURY OR FIRE.**
 14. Dispose of expended battery's properly. The Lincoln Model 1201 Battery Pack contains rechargeable, nickel-cadmium batteries. These batteries must be recycled or disposed of properly. Drop off expended battery packs at your local replacement battery retailer, or your recycling center.
- * New batteries are shipped in an uncharged state and the initial charge will require 12 hours before use.

15. Charging time will be approximate 1 hour after the initial charge.
 - a.) The red fast charge indicator will stay lit until the battery is near full charge.
 - b.) The green trickle charge indicator will light and stay lit until battery is removed from charger.

Do not leave battery plugged into charger for extended period of time after charged.

Note: If the red fast charge indicator is turning "on" and "off" frequently, it is an indication of a bad battery, remove battery from charger and replace the battery.

Users in the United States NOTE:

Applicable fees for the collection and recycling of these batteries have been paid to the RBRCTM. For further information, call 1-800-8BATTERY.

Product Specifications

	Model 1215	Model 1215A
Input Voltage	12 Volts @ 3 amps	12/24 Volts @ 3/1.25 amps©
Output	14.5 Volts @ 2.5 Amps	14.5 Volts @ 2.5 Amps
Time to Charge		
1201 Battery:	1 Hour	1 Hour
Cord Length	6 ft (2 m)	6 ft (2 m)
Indicator Lights	Red (Charging) Green (Complete)	Red (Charging) Green (Complete)
Weight	1 lb. (.45 Kg)	1 lb. (.45 Kg)

Note: Plug fits 12 V or 24 V cigarette lighter sockets.



Americas:
One Lincoln Way
St. Louis, MO 63120-1578
USA
Phone +1.314.679.4200
Fax +1.800.424.5359

Europe/Africa:
Heinrich-Hertz-Str 2-8
D-69183 Walldorf
Germany
Phone +49.6227.33.0
Fax +49.6227.33.259

Asia/Pacific:
25 Int'l Business Park
#01-65 German Centre
Singapore 609916
Phone +65.562.7960
Fax +65.562.9967

© Copyright 2004
Printed in USA

Web site:
www.lincolnindustrial.com

Models 1215 & 1215A

PowerLuber Battery Charger

LINCOLN

~~Declaration of conformity according to EMV directive 89/336/EEG as last amended by EC Directive 93/68/EEG Electro-~~
magnetic Compatibility.©

We declare that the model of the
Battery Charger
in the version supplied by us, complies with the provisions of the above mentioned directive.

Applied harmonized standards in particular:

- EN61000-3-3 Electromagnetic Compatibility (EMC) - Part 3: Limits - Section 3: Limitations of Voltage Fluctuations and Flicker in Low Voltage Supply Systems for Equipment with Rated Current = 16A - SAME AS IEC 61000-3-3
- EN 55014-2 Electromagnetic Compatibility - Requirements for Household Appliances, Electric Tools, & Similar Apparatus - Part 2: Immunity - Product Family Standard
- EN55014-1 Electromagnetic Compatibility - Requirements for Household Appliances, Electric Tools and Similar Apparatus - Part 1: Emission - Product Family Standard
- EN 61000-3-2 + Amendment 1, + Amendment 2, + Amendment 14 Electromagnetic Compatibility (EMC) Part 3: Limits - Section 2: Limits for Harmonic Current Emissions (Equipment Input Current <= 16A per Phase)



St. Louis, MO 01/07/04, Paul Conley, Chief Engineer

Lincoln Industrial Standard Warranty

LIMITED WARRANTY

Lincoln warrants the equipment manufactured and supplied by Lincoln to be free from defects in material and workmanship for a period of one (1) year following the date of purchase, excluding there from any special, extended, or limited warranty published by Lincoln. If equipment is determined to be defective during this warranty period, it will be repaired or replaced, within Lincoln's sole discretion, without charge.

This warranty is conditioned upon the determination of a Lincoln authorized representative that the equipment is defective. To obtain repair or replacement, you must ship the equipment, transportation charges prepaid, with proof of purchase to a Lincoln Authorized Warranty and Service Center within the warranty period.

This warranty is extended to the original retail purchaser only. This warranty does not apply to equipment damaged from accident, overload, abuse, misuse, negligence, faulty installation or abrasive or corrosive material, equipment that has been altered, or equipment repaired by anyone not authorized by Lincoln. This warranty applies only to equipment installed, operated and maintained in strict accordance with the written specifications and recommendations provided by Lincoln or its authorized field personnel.

THIS WARRANTY IS EXCLUSIVE AND IS IN LIEU OF ANY OTHER WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE WARRANTY OF MERCHANTABILITY OR WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE.

In no event shall Lincoln be liable for incidental or consequential damages. Lincoln's liability for any claim for loss or damages arising out of the sale, resale or use of any Lincoln equipment shall in no event exceed the purchase price. Some jurisdictions do not allow the exclusion or limitation of incidental or consequential damages, therefore the above limitation or exclusion may not apply to you.

This warranty gives you specific legal rights. You may also have other rights that vary by jurisdiction.

Customers not located in the Western Hemisphere or East Asia: Please contact Lincoln GmbH & Co. KG, Walldorf, Germany, for your warranty rights.

Lincoln Industrial Contact Information

To find Lincoln Industrial's Nearest Service Center call the following numbers, or you may also use our website

Customer Service	314-679-4200
Website	lincolnindustrial.com